

**Lecture 1 Sample Problem Solutions**

---

**Problem 1.1**

$$x[n] = -\sin\left(\frac{3\pi n}{5}\right) + 3\cos\left(\frac{2\pi n}{5}\right)$$

**Problem 1.2**

$$X(j\Omega) = -j\pi\delta(\Omega - 14000\pi) + j\pi\delta(\Omega + 14000\pi) + 3\pi\delta(\Omega - 16000\pi) + 3\pi\delta(\Omega + 16000\pi)$$

Sketch should show delta functions at  $\pm 14000\pi$  and  $\pm 16000\pi$  with areas of  $-j\pi$ ,  $j\pi$ ,  $3\pi$ , and  $3\pi$ .

$$X(e^{j\omega}) = j\pi\delta\left(\omega - \frac{3\pi}{5}\right) - j\pi\delta\left(\omega + \frac{3\pi}{5}\right) + 3\pi\delta\left(\omega - \frac{2\pi}{5}\right) + 3\pi\delta\left(\omega + \frac{2\pi}{5}\right)$$

Sketch should show delta functions at  $\pm 3\pi/5$  and  $\pm 2\pi/5$  with areas of  $-j\pi$ ,  $j\pi$ ,  $3\pi$ , and  $3\pi$ .

**Problem 1.3**

$$X(j\Omega) = \left(\frac{1}{2j}\right) \frac{1}{100\pi + j(\Omega - 1000\pi)} - \left(\frac{1}{2j}\right) \frac{1}{100\pi + j(\Omega + 1000\pi)}$$

Sketch should show peaks at  $\approx \pm 1000\pi$  with amplitudes of  $1/200\pi$  and bandwidths of  $200\pi$ .

**Problem 1.4**

$$X(e^{j\omega}) = \left(\frac{1}{2j}\right) \frac{1}{1 - e^{-\left(\frac{\pi}{20} + j(\omega - \frac{\pi}{2})\right)}} - \left(\frac{1}{2j}\right) \frac{1}{1 - e^{-\left(\frac{\pi}{20} + j(\omega + \frac{\pi}{2})\right)}}$$

Sketch should show peaks at  $\approx \pm \pi/2$  with amplitudes of  $10/\pi$  and bandwidths of  $\pi/10$ .