

Problem 1

Suppose we have an LTI system with an input disturbance:

$$\dot{x} = Ax + B(u + w)$$

$$y = Cx$$

If we knew $w(t)$, we could control the system with $u(t) = -w(t) - K\hat{x}(t)$, where $\hat{x}(t)$ is our state estimate from some observer.

However, we don't know $w(t)$. Suppose that we know the dynamics of $w(t)$:

$$\dot{z} = A_m z$$

$$w = C_m z$$

Thus, we know A_m, C_m , but not the value of z or w . Let's augment our state-space model as follows:

$$\begin{bmatrix} \dot{x} \\ \dot{z} \end{bmatrix} = \begin{bmatrix} A & BC_m \\ 0 & A_m \end{bmatrix} \begin{bmatrix} x \\ z \end{bmatrix} + \begin{bmatrix} B \\ 0 \end{bmatrix} u$$

$$y = [C \quad 0] x$$

- Is the new system controllable?
- Derive a full-state observer for this augmented system. Leave the observer gain as $L = \begin{bmatrix} L_1 \\ L_2 \end{bmatrix}$.
- Use the state estimate from this observer for a control law $u = -C_m \hat{z} - K\hat{x}$. (Note that our estimate of the unknown noise term w is $C_m \hat{z}$.) Write out the dynamics of the controller and observer, viewing y as the input to this system and u as the output. What are the eigenvalues of these 'controller and observer' dynamics? (Again, leave the controller gain as K .)
- Write out the closed-loop dynamics for the controller, observer, and original system, using the states (x, z, \hat{x}, \hat{z}) .

Problem 2

Suppose we have the same setup as the previous problem, with system dynamics given by

$$\dot{x} = Ax + B(u + w)$$

$$y = Cx$$

and noise dynamics given by

$$\dot{z} = A_m z$$

$$w = C_m z$$

Rather than explicitly estimate the unknown state, let's filter the output. Let's add the following states:

$$\dot{x}_a = A_m^T x_a + C_m^T y$$

- Derive an observer for \hat{x} , ignoring the w term. Again, leave L in the equations without explicitly calculating these values.
- Stabilize the system with $u = -K_1 \hat{x} - K_2 x_a$. Derive the dynamics for your controller and filter (\hat{x}, x_a) , viewing y as an input and u as the output.
- What are the eigenvalues of your 'controller and filter' dynamics?